

# Datasheet



0370 330 6021 www.sunbeltrentals.co.uk

# PT18-10 PT30-10

# High Voltage DC Cable \_\_\_\_\_ Test Systems



#### **Features**

- ±18kVdc output voltage (PT18-10)
  ±30kVdc output voltage (PT30-10)
- 10mA output capability
- Both voltage and current metered on HV outputs
- Automatic earth system for dumping capacitive loads
- HV output plug & socket system
- Key operated supply switch to prevent unauthorised operation
- Zero-volt interlock
- Visual indication of test piece failure

T&R Test Equipment is a market leader in the field of protection test equipment. The range includes primary and secondary current injection equipment up 6000A, voltage sources, micro-ohmmeters and high voltage test systems up to 100kV.

The PT18-10 and PT30-10 high voltage dc test sets are designed to perform tests on installed cable and jointing systems. The units have a variable output voltage with a maximum or  $\pm 18$ kVdc (PT18-10) or  $\pm 30$ kVdc (PT30-10). Both units have a maximum charging capability of 10mA. A zero-volt interlock is fitted that prevents the output being switched on unless the output control is at zero.

The units include an automatic load discharge system that discharges the cable under test when the output is switched off or a breakdown occurs. The internal dumping system can discharge a maximum of 2.5kJ on each output, corresponding to  $10\mu$ F at 18kV or  $4\mu$ F at 30kV. In the event of a test object failure, the overload circuit will automatically switch off the output voltage and earth the output via the internal discharge circuit. A manual discharge probe is also supplied as standard with both units, allowing higher load capacitances to be safely discharged.

The output voltage is metered by two large, linear, analogue instruments marked 0-20kV (PT18-10) or 0-30kV (PT30-10).

2 lest Equip

Test object current is metered by two further analogue instruments with 0-10 scale marking. The meters read 0-10mA directly, or 0-1mA when the  $\pm$ 10 push button is operated.

The HV output from the unit uses a high quality plug and socket system,

allowing for easy cable replacement.

A range of AC & DC high v o I t a g e systems are available from T&R Test E q u i p m e n t with outputs up to ±30kV dc and 100kV ac.

| Unit type | Voltage | Current |
|-----------|---------|---------|
| PT15-10S  | -15kVdc | 10mA    |
| PT18-10   | ±18kVdc | 10mA    |
| PT30-10   | ±30kVdc | 10mA    |
| KV5-100   | 5kVac   | 100mA   |
| KV15-80   | 15kVac  | 80mA    |
| KV30-40   | 30kVac  | 40mA    |
| KV30-100  | 30kVac  | 100mA   |
| KV50-100  | 50kVac  | 100mA   |
| KV50-200  | 50kVac  | 200mA   |
| KV100-100 | 100kVac | 100mA   |



KV50-100





#### PT18-10 & PT30-10 Specification

#### Output

All of the PT series cable test systems have high quality high voltage output connectors, and are supplied with detachable, partially screened output cables

| Unit type | Voltage    | Continuous | 5 minutes |
|-----------|------------|------------|-----------|
| PT18-10   | 0 to ±18kV | 5mA        | 10mA      |
| PT30-10   | 0 to ±30kV | 5mA        | 10mA      |

The above intermittent on times must be followed by an off time of 15 minutes, and is based on an ambient temperature of  $25^{\circ}$ C.

#### Metering

The positive and negative output voltages on the PT series are metered on the HV output by separate analogue instruments.

| Unit    | Range  | Accuracy            |
|---------|--------|---------------------|
| PT18-10 | 0-20kV | ±1.5% of full scale |
| PT30-10 | 0-30kV | ±1.5% of full scale |

The output current on both of the outputs is metered by a dual range analogue instrument. The 1mA range is selected by the  $\div$ 10 pushbutton adjacent to the mA meter.

| Unit    | Range | Accuracy            |
|---------|-------|---------------------|
| PT18-10 | 10mA  | ±2.5% of full scale |
|         | 1mA   | ±2.5% of full scale |
| PT30-10 | 10mA  | ±2.5% of full scale |
|         | 1mA   | ±2.5% of full scale |

#### **Overload Protection**

The PT18-10 and PT30-10 are protected by an overload trip on the output that operates at 12mA.

#### Load Discharge System

The PT18-10 and PT30-10 are fitted with an automatic internal load discharge system that grounds the load via a  $20k\Omega$  resistor on each output when the output is switched off. The discharge system is rated to dissipate 2.5kJ once every 15 minutes on each output. The PT18-10 can discharge a maximum load capacitance of  $10\mu$ F per output from 18kV, and the PT30-10 can discharge a maximum load capacitance of  $4\mu$ F per output from 30kV.

| Unit                          | PT18-10 | PT30-10 |
|-------------------------------|---------|---------|
| Maximum discharge energy      | 2.5kJ   | 2.5kJ   |
| Maximum discharge capacitance | 10μF    | 4μF     |
| from max output voltage       |         |         |

The PT series units are supplied with a DP20 or DP40 manual discharge probe to allow the discharge of higher capacitance loads.

|                               | PT18-10 | PT30-10     |
|-------------------------------|---------|-------------|
| Discharge probe supplied      | DP20    | DP40        |
| Resistance                    | 30kΩ    | $60k\Omega$ |
| Maximum discharge energy      | 3.6kJ   | 7.2kJ       |
| Maximum discharge capacitance | 15μF    | 11μF        |
| from max output voltage       |         |             |

Supply Requirements

| PT18-10 | 115V±10% 50/60Hz 1ph 600VA max |
|---------|--------------------------------|
|         | 240V±10% 50/60Hz 1ph 600VA max |

PT30-10 115V±10% 50/60Hz 1ph 1000VA max 220V±10% 50/60Hz 1ph 1000VA max 240V±10% 50/60Hz 1ph 1000VA max

#### Protection and Safety

The output of the unit is protected by an overload trip, and the input and control supplies are protected by fuses.

The PT18-10 and PT30-10 are designed to meet the requirements of BS EN61010.

An earth terminal is provided on the units which must be connected to a low impedance local earth.

#### Temperature Range

Storage -20°C to 60°C Operating 0°C to 45°C

| Dimensions |               | Weight |
|------------|---------------|--------|
| PT18-10    | 471x144x362mm | 17kg   |
| PT30-10    | 471x191x362mm | 25kg   |

#### Accessories

Supply lead, spare fuse, operating manual, output leads, DP20/ DP40 discharge probe, earth lead.





PT18-10

DP20 Discharge probe

PT30-10

# We are supporting you to deliver a world class service, every day, in every sector...

# LOCATIONS

### LONDON, HEATHROW

Sunbelt Rentals UK Test & Monitoring 242-252 London Road, Staines, London TW18 4JQ 0333 122 3126 www.sunbeltrentals.co.uk/find-a-depot/london-heathrow

### REDCAR

Sunbelt Rentals UK Test & Monitoring Unit 5 Kirkleatham Business Park, Redcar TS10 5SQ 0370 330 6021 www.sunbeltrentals.co.uk/find-a-depot/teesside

### STOKESLEY

Sunbelt Rentals UK Test & Monitoring 2 Ellerbeck Way, Stokesley Business Park, Stokesley, North Yorkshire TS9 5JZ 01642 718 900 www.sunbeltrentals.co.uk/find-a-depot/stokesley



### www.inlec.com

Order Online with Next Day Delivery, Online Chat & Online Account Management



## ★ Trustpilot

View our trustpilot score  $\star$   $\star$   $\star$ 

• HEATHROW



