EUROPE'S LARGEST SELECTION OF TEST & MEASUREMENT EQUIPMENT FOR HIRE

# INLEC.COM

WHEN YOU CAN HIRE

# 

Nationwide Low Call 0333 6000 600

# Megger.

# **DLRO 200** Digital Microhmmeter



- Small and weighs less than 15kg
- Test currents from 10 A to 200 A d.c.
- 0.1 μΩ best resolution
- On board memory for up to 300 test results and notes
- RS232 port to download stored results or for real time output to a printer
- Supplied complete with 5m test leads and download software

# DESCRIPTION

Megger DLRO200 measures resistances between 0.1  $\mu\Omega$  and 1  $\Omega,$  at high currents.

This versatile instrument can provide test currents from 10 amps up to 200 amps subject to the load resistance and supply voltage. A large liquid crystal display provides all the information needed to perform a test; all test parameters and measurement results are displayed.

The unique design allows the weight and size of DLRO200 to be kept to a minimum; the instrument weighs less than 15kg. This small size makes DLRO200 equally at home in the workshop, on the production floor or in the field. The high current capability and compact design make DLRO200 suitable for testing circuit breaker contacts, switch contacts, busbar joints or other applications where high current is needed.

300 sets of results may be stored in DLRO200's on board memory for later download to a PC or may be output directly to a printer via the RS232 port. You may also add notes to any stored result by using the on board alphanumeric keypad, thereby making later identification of results straightforward.

As well as adding notes to stored results, the alphanumeric keypad allows you to set the test current directly by typing in the value required. DLRO200 will check the continuity of the test circuit, and will quickly ramp the test current up to the desired level. The keyboard is also used to set upper and lower limits for the result and to prevent the use of excessive currents by setting an upper limit to the allowable test current.

DLRO200 uses a four terminal measurement technique to cancel

the resistance of the test leads from the measurement.

DLRO200 operates in one of three modes, which are simply selected from the on screen menu.

CONTINUOUS mode is provided for users who wish to monitor a resistance over a period of time. Connect the test leads, select the test current and press the TEST button. DLRO200 will pass a current continuously, and measure the resulting voltage at 2 second intervals, until the test button is pressed to stop the test or the test circuit is interrupted.

In NORMAL mode you connect the leads, select the test current and press the TEST button. The test current will ramp up to the desired level, hold for 2 seconds and then ramp down. The whole process takes approximately 10 seconds.

In AUTO mode select the desired current, connect the current leads and press the TEST button. The TEST lamp will flash to show that the DLRO200 is ready to carry out a test. As soon as the potential leads are connected, a test will start. To repeat a test, simply break contact with the voltage probes and remake contact.

Measuring individual joints in a busbar is a good example of the convenience to be gained by using AUTO mode. The two current leads are connected to the ends of the busbar. They will remain connected here until all tests have been completed. When the voltage leads make contact across a joint, DLRO200 detects that all four leads are connected, carries out a test and stops. When you move to the next joint DLRO detects the new completed circuit automatically and carries out the next test, and so on until all joints have been tested. The results may be stored automatically and may be recalled to the display or downloaded for review.



# **SPECIFICATIONS**

### **Measurement:**

**Range:**  $0.1 \,\mu\Omega$  to 999.9 m $\Omega$ (Subject to supply voltage and leads used)

### Accuracy:

Voltage	$\pm 0.5\%$ $\pm$ 0.1 mV
Current	$\pm 0.5\%$ $\pm$ 0.1 A
Resistance:	Better than 1% from
	$100 \ \mu\Omega$ to $100 \ m\Omega$

### **Current Lead Resistance (Megger supplied leads)**

$2 \ge 5 \mod 25 \mod^2$ current leads	$8 \text{ m}\Omega$
$2 \text{ x} 5 \text{ m} 50 \text{ mm}^2$ current leads	$4~\mathrm{m}\Omega$
$2 \ge 10 \text{ m} 70 \text{ mm}^2$ current leads	$5.4~\mathrm{m}\Omega$
$2 \ge 15 \text{ m} 95 \text{ mm}^2$ current leads	$6~\mathrm{m}\Omega$

# **Maximum Continuous Test Time**

More than 10 minutes at 200 A @ 20°C ambient.

## **Power Supply DLRO200**

for full output (unsmoothed d.c.):			
100 to 265 V 50/60 HZ w	vith a load		
less than 19 m $\Omega$ (supply	>207 V rms), or		
$11 \text{ m}\Omega \text{ (}115 \text{ V rms)}  inclu$	ding current leads		

**ORDERING INFORMATION** 

# Power Supply DLRO200-115

for full output (additional smoothing):

	100 to 130 V 50/60 HZ with a load less than 11 m $\Omega$ including current leads
Test Modes:	Manual, Auto, Continuous.
Test Time:	10 seconds NORMAL /AUTO mode. Refreshed every 2 seconds in CONTINUOUS mode
Display:	Large, high resolution backlit liquid crystal display
Warnings	Current flowing: - LED. Other warnings are shown on the lcd display.

Data Transfer	Real time or batch download via RS232				
	using Download Manager.				
Storage Capacity	Storage Capacity:				
	300 result sets and memo, battery backed for				
	10 years.				
Memo field:	160 characters max.				
Test Current					
Range:	10 A to 200 A d.c. *				
Accuracy:	$\pm 2\% \pm 2$ A				
Voltmeter input					
	$>200 \text{ k}\Omega$				
Hum rejection:					
Temperature					
<b>Operation:</b>	-10 to +50°C				
Storage:	-25 to +65°C				
Calibration:	20°C				
Co-efficient:	<0.05% per °C				
Max. Humidity:	95% RH non-condensing				
Maxi Altitude:	2000 m				
Safety:	IEC61010 – (1995)				
EMC:	EN61326 annex A (heavy industrial)				
	/·· · · · · · · · · · · · · · · · · · ·				
Dimensions:	410 x 250 x 270 mm				
Weight:	14.5 kg (excluding test leads)				

\* DLRO200-115 supplied with 25 mm<sup>2</sup> current leads 6220-787 as standard

ltem (Qty)	Order No.	ltem (Qty)	Order No.
DLRO200 High Current Digital Low Resistance		EQuick Start Guide (French)	6172-783
Ohmmeter (English QWERTY keyboard)	DLRO200 E	Warranty card.	6170-618
DLRO200 High Current Digital Low Resistance		Optional Accessories at extra cost	
Ohmmeter (French AZERTY keyboard)	DLRO200 F	*5m Lead set in bag comprising:	6220-787
DLRO200-115 High Current Digital Low Resistance		2 x 25mm <sup>2</sup> current leads with clamps and	
Ohmmeter 115 V (English QWERTY keyboard)	DLRO200-115 E	2 x potential leads with clips.	
Included Accessories		15m Lead set comprising 2 x 95 mm <sup>2</sup>	
5 m Lead set comprising 2 x 50 mm <sup>2</sup>		current leads with clamps and	
current leads with clips and 2 potential		2 x potential leads with clips.	6220-757
leads with clips	6220-755	10m Lead set comprising 2 x 95 mm <sup>2</sup>	
Download Manager	6111-442	current leads with clamps and	
User Guide on CD-ROM	6172-763	2 x potential leads with clips.	6220-756
RS232 download cable	25955-025		
Quick Start Guide (English)	6172-782		

UK

Archcliffe Road Dover CT17 9EN England T +44 (0) 1304 502101 F +44 (0) 1304 207342

UNITED STATES 4271 Bronze Way Dallas TX 75237-1088 USA T 800 723 2861 (USA only) T +1 214 333 3201 F +1 214 331 7399

### OTHER TECHNICAL SALES OFFICES Norristown USA, Toronto CANADA,

Mumbai INDIA, Trappes FRANCE, Sydney AUSTRALIA, Madrid SPAIN and the Kingdom of BAHRAIN.

Registered to ISO 9001:2000 Reg no. Q 09290 Registered to ISO 14001 Reg no. EMS 61597 DLRO200\_DS\_en\_V01

www.megger.com Megger is a registered trademark

# INLEC, supporting you to deliver a world class service, every day, in every sector ...



# **OUR COMMITMENT TO YOU**

# A wealth of knowledge and experience.

You can take advantage of expert advice to ensure you get the best, most appropriate and cost effective equipment for the job. We supply a wide variety of industries, so if there is another way to do the job or save you time and money we'll pass on the benefit of our experience for free.

# Honest advice, just a phone call away.

If we don't have a particular item, rather than hiring you something that won't do the job, we would rather direct you to an alternative supplier. You will always be provided with full instructions and if you still need help, call our technical team on Nationwide Low Call 0333 6000 600. Our aim is to save you time, frustration and money.

# Top quality equipment from major manufacturers.

With Inlec you'll get the most accurate, reliable and wellmaintained equipment available. Prices are regularly reviewed to ensure you always enjoy the best value for money. We have made a significant investment in test equipment so we ensure that it's well packed to minimise damage and delay.

# We really do listen to you.

You won't waste your time contacting Inlec. Every request for equipment is logged and carefully considered. Listening to our customers helps keep our product range up to date and relevant. If you are unhappy about any aspect of our service please let us know so we can put it right.

# **YOUR 5 WAY GUARANTEE**

# **O GUARANTEE SAME DAY DESPATCH**

We understand why prompt delivery is important to you. So, if we confirm your order before 3pm, you are guaranteed same day despatch.

# **2 OUR PRICE GUARANTEE**

Inlec guarantee you real value for money. Our price match policy is simple - if you can hire the same product for less elsewhere, we guarantee to match that price and reduce it by a further 10% of the difference - and still deliver our industry leading technical and customer support.

For full details check our price-match guarantee online

# **O TOP QUALITY GUARANTEED**

All equipment is thoroughly checked prior to dispatch to ensure you receive it in full, safe working order. Your shipment will be securely packed and include manufacturer's instructions, accessories or consumables and a valid calibration certificate where appropriate. In addition, Inlec offer a 24 hour replacement service if you decide the equipment is not suitable for your application\*.

# FRIENDLY, KNOWLEDGEABLE ADVICE GUARANTEED

Inlec are happy to provide you with free advice, from anunbeatable team of experienced, knowledgeable and friendly engineers and hire experts.

# **S** YOUR GUARANTEE OF THE BEST CUSTOMER SERVICE

Throughout your hire we will work hard to ensure you enjoy the very best in support and service from Inlec. We guarantee you won't find better service anywhere in the industry.

\*subject to availability and conditions

# **Europe's leading Test Equipment Hire Specialist**



Nationwide Low Call 0333 6000 600 Online: www.inlec.com





Inlec UK Ellerbeck Way, Stokesley Business Park, Stokesley N Yorkshire TS9 5JZ United Kingdom